


## BSP Taper Female Adapter For fractional tube




| CPI™<br>PART NO. | A-LOK®<br>PART NO. | INTER-<br>CHANGES<br>WITH | INCHES       |                |      |     |          |      |
|------------------|--------------------|---------------------------|--------------|----------------|------|-----|----------|------|
|                  |                    |                           | TUBE<br>O.D. | BSPT<br>THREAD | A    | K   | W<br>HEX | BORE |
| 4-2K T2HG        | 4FA2K              | 4-TR-7-2RT                | 1/4          | 1/8-28         | 1.31 | .64 | 9/16     | .156 |
| 4-4K T2HG        | 4FA4K              | 4-TR-7-4RT                | 1/4          | 1/4-19         | 1.48 | .64 | 3/4      | .156 |
| 6-4K T2HG        | 6FA4K              | 6-TR-7-4RT                | 3/8          | 1/4-19         | 1.56 | .72 | 3/4      | .281 |
| 6-6K T2HG        | 6FA6K              | 6-TR-7-6RT                | 3/8          | 3/8-19         | 1.63 | .72 | 7/8      | .281 |
| 8-4K T2HG        | 8FA4K              | 8-TR-7-4RT                | 1/2          | 1/4-19         | 1.83 | .98 | 3/4      | .375 |
| 8-6K T2HG        | 8FA6K              | 8-TR-7-6RT                | 1/2          | 3/8-19         | 1.89 | .98 | 7/8      | .375 |
| 8-8K T2HG        | 8FA8K              | 8-TR-7-8RT                | 1/2          | 1/2-14         | 2.14 | .98 | 1-1/16   | .375 |

NOTE: Tube stub is pre-grooved as standard.

Dimensions for reference only, subject to change.

Generic (non-grooved) can be ordered through Quick Response Department.  
Add -Z6 for assembly of nuts and ferrules on the tube stub end.

## BSP Taper Female Adapter For metric tube



| CPI™<br>PART NO. | A-LOK®<br>PART NO. | INTER-<br>CHANGES<br>WITH | MILLIMETERS  |                |      |      |          |      |
|------------------|--------------------|---------------------------|--------------|----------------|------|------|----------|------|
|                  |                    |                           | TUBE<br>O.D. | BSPT<br>THREAD | A    | K    | W<br>HEX | BORE |
| T2HG 3-1/8K      | M3FA1/8K           | 3-MTA-7-2RT               | 3            | 1/8            | 27,8 | 13,5 | 14,0     | 1,8  |
| T2HG 4-1/8K      | M4FA1/8K           | 4-MTA-7-2RT               | 4            | 1/8            | 28,6 | 14,3 | 14,0     | 2,0  |
| T2HG 6-1/8K      | M6FA1/8K           | 6-MTA-7-2RT               | 6            | 1/8            | 30,2 | 15,9 | 14,0     | 4,0  |
| T2HG 8-1/4K      | M8FA1/4K           | 8-MTA-7-4RT               | 8            | 1/4            | 39,1 | 16,7 | 19,0     | 6,4  |
| T2HG 10-1/4K     | M10FA1/4K          | 10-MTA-7-4RT              | 10           | 1/4            | 36,5 | 17,5 | 19,0     | 7,5  |
| T2HG 10-3/8K     | M10FA3/8K          | 10-MTA-7-6RT              | 10           | 3/8            | 31,8 | 17,5 | 22,0     | 7,5  |
| T2HG 10-1/2K     | M10FA1/2K          | 10-MTA-7-8RT              | 10           | 1/2            | 41,3 | 17,5 | 27,0     | 7,5  |
| T2HG 12-1/4K     | M12FA1/4K          | 12-MTA-7-4RT              | 12           | 1/4            | 40,5 | 23,0 | 19,0     | 9,1  |
| T2HG 12-3/8K     | M12FA3/8K          | 12-MTA-7-6RT              | 12           | 3/8            | 43,7 | 23,0 | 22,0     | 9,1  |
| T2HG 12-1/2K     | M12FA1/2K          | 12-MTA-7-8RT              | 12           | 1/2            | 46,8 | 23,0 | 27,0     | 9,1  |
| T2HG 16-1/2K     | M16FA1/2K          | 16-MTA-7-8RT              | 16           | 1/2            | 48,4 | 24,6 | 27,0     | 12,7 |
| T2HG 18-3/4K     | M18FA3/4K          | 18-MTA-7-12RT             | 18           | 3/4            | 51,6 | 24,6 | 32,0     | 14,0 |
| T2HG 20-3/4K     | M20FA3/4K          | 20-MTA-7-12RT             | 20           | 3/4            | 52,4 | 25,4 | 32,0     | 15,1 |
| T2HG 25-1K       | M25FA1K            | 25-MTA-7-16RT             | 25           | 1              | 66,7 | 31,8 | 41,0     | 19,8 |

NOTE: Tube stub is pre-grooved as standard.

Dimensions for reference only, subject to change.

Add -Z6 for assembly of nuts and ferrules on the tube stub end.